

UTILITY PATENT

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re U.S. Patent No. 7,646,831	)	Serial No. 09/981,795
	)	
Inventor(s): Markus SCHETELIG, et al.	)	Filed: October 19, 2001
	)	
Issue Date: January 12, 2010	)	Attorney Docket No. 006916.00007

For: METHOD AND A DEVICE FOR CONTROLLING DATA EXTRACTION FROM A DATA STREAM CONTAINING AT LEAST ONE DATA PACKET

**REQUEST FOR CERTIFICATE OF CORRECTION**

U.S. Patent and Trademark Office  
Customer Service Window  
Randolph Building, Mail Stop: Certificate of Correction Branch  
401 Dulany Street  
Alexandria, VA 22314

Sir:

Pursuant to 35 U.S.C. § 254 and 37 C.F.R. § 1.322, this is a request for the issuance of a Certificate of Correction in the above-identified patent. A copy of PTO Form 1050 is appended. The complete Certificate of Correction involves 1 page.

The mistake identified in the appended Form occurred through no fault of the Applicants, as clearly disclosed by the records of the application, which matured into this patent. Enclosed for your convenience is the Specification filed October 19, 2001.

Issuance of the Certificate of Correction containing the correction is respectfully requested. Since this change is necessitated through no fault of the Applicants, no fee is believed to be associated with this request. Nonetheless, should the Patent and Trademark Office determine that a fee is required, please charge our Deposit Account No. 19-0733.

Respectfully submitted,

BANNER & WITCOFF, LTD.

Dated: April 23, 2010  
Banner & Witcoff, Ltd  
1100 13<sup>th</sup> Street, N.W., Suite 1200  
Washington, D.C. 20005-4051  
(202) 824-3000

By: /Kenneth Smolik/  
Kenneth Smolik  
Registration No. 44, 344

UNITED STATES PATENT AND TRADEMARK OFFICE  
**CERTIFICATE OF CORRECTION**

PATENT NO.: 7,646,831  
DATED: January 12, 2010  
INVENTOR(S): Markus SCHETELIG, et al.

It is certified that an error appears in the above-identified patent and that said Letters Patent is hereby corrected as shown below:

In Title,  
Please delete "Lease" and insert --Least--

Mailing Address of Sender:

Banner & Witcoff, Ltd.  
1100 13<sup>th</sup> Street, N.W., Suite 1200  
Washington, DC 20005-4051

U.S. PAT. NO 7,646,831

No. of add'l copies  
@ \$0.50 per page

□

Please type a plus sign (+) inside this box →

+

PTO/SB/05 (03-01)

Approved for use through 10/31/2002. OMB 0651-0032

U.S. Patent and Trademark Office: U.S. DEPARTMENT OF COMMERCE

Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it displays a valid OMB control number.

**UTILITY  
PATENT APPLICATION  
TRANSMITTAL**

(Only for new nonprovisional applications under 37 CFR 1.53(b))

Attorney Docket No.

1117.40738X00

First Inventor

SCHETELIG, MARKUS

Title

A METHOD AND A DEVICE FOR CONTROLLING DATA  
EXTRACTION FROM A DATA STREAM CONTAINING AT  
LEAST ONE DATA PACKET

Express Mail Label No.

**APPLICATION ELEMENTS**

SEE MPEP chapter 600 concerning utility patent application contents.

**ADDRESS TO:**

Assistant Commissioner for Patents  
Box Patent Application  
Washington, DC 20231

1. ☒ Fee Transmittal Form (e.g., PTO/SB/17)  
(Submit an original and a duplicate for fee processing)

2. ☐ Applicant claims small entity status.  
See 37 CFR 1.27

3. ☒ Specification [Total Pages: 19]  
(preferred arrangement set forth below)

-Descriptive title of the invention  
-Cross Reference to Related Applications  
-Statement Regarding Fed sponsored R & D  
-Reference to sequence listing, a table,  
or a computer program listing appendix  
-Background of the invention  
-Brief Summary of the invention  
-Brief Description of the Drawings (if filed)  
-Detailed Description  
-Claim(s)  
-Abstract of the Disclosure

4. ☒ Drawing(s) (35 U.S.C. 113) [Total Pages: 3]

5. Oath or Declaration [Total Pages: \_\_\_\_]

- a. ☐ Newly executed (original or copy)  
b. ☐ Copy from a prior application (37 CFR 1.63 (d))  
(for continuation/divisional with Box 18 completed)

☐ **DELETION OF INVENTOR(S)**  
Signed statement attached deleting inventor(s)  
Named in the prior application, see 37 CFR  
1.63(d)(2) and 1.33(b)

6. ☐ Application Data Sheet. See 37 CFR 1.78

7. ☐ CD-ROM or CD-R in duplicate, large table or  
Computer Program (Appendix)  
8. Nucleotide and/or Amino Acid Sequence Submission  
(if applicable, all necessary)

- a. ☐ Computer Readable Form (CRF)

- b. Specification Sequence Listing on:

i. ☐ CD-ROM or CD-R (2 copies); or

ii. ☐ paper

- c. ☐ Statements verifying identity of above copies

**ACCOMPANYING APPLICATION PARTS**

9. ☐ Assignment Papers (cover sheet & documents(s))  
10. ☐ 37 CFR 3.73(b) Statement ☐ Power of Attorney  
(when there is an assignee)  
11. ☐ English Translation Document (if applicable)  
12. ☒ Information Disclosure ☐ Copies of IDS Citations  
Statement (IDS)/PTO-1449  
13. ☒ Preliminary Amendment  
14. ☒ Return Receipt Postcard (MPEP 503)  
(Should be specifically itemized)  
15. ☐ Certified Copy of Priority Document(s)  
(if foreign priority is claimed)  
16. ☐ Nonpublication Request under 35 U.S.C. 122  
(b)(2)(B)(i). Applicant must attach form PTO/SB/35  
or its equivalent.  
17. ☒ Other **Figs. 1-5, Credit Card Payment Form**

18. If a CONTINUING APPLICATION, check appropriate box, and supply the requisite information below and in a preliminary amendment, or in an Application Data Sheet under 37 CFR 1.76:

☐ Continuation ☐ Divisional ☐ Continuation-in-part (CIP) of prior application No.:

Prior application information: Examiner: \_\_\_\_\_ Group Art Unit: \_\_\_\_\_

For CONTINUATION OR DIVISIONAL APPS only: The entire disclosure of the prior application, from which an oath or declaration is supplied under Box 5b, is considered a part of the disclosure of the accompanying continuation or divisional application and is hereby incorporated by reference. The incorporation can only be relied upon when a portion has been inadvertently omitted from the submitted application parts.

**19. CORRESPONDENCE ADDRESS**

☒ Customer Number or Bar Code Label

020457

or ☐ Correspondence address below

(Insert Customer No. or Attach bar code label here)

Name **ANTONELLI, TERRY, STOUT & KRAUS, LLP**

Address

City

State

Zip  
Code

Country

Telephone

(703) 312-6600

Fax

(703) 312-6666

Name

Carl J. Brundidge

Registration No. (Attorney/Agent)

29,621

Signature

Date

October 19, 2001

Burden Hour Statement: This form is estimated to take 2 hours to complete. Time will vary depending upon the needs of the individual case. Any comments on the amount of time you are required to complete this form should be sent to the Chief Information Officer, U.S. Patent and Trademark Office, Washington, DC 20231. DO NOT SEND FEES OR COMPLETED FORMS TO THIS ADDRESS. SEND TO: Assistant Commissioner for Patents, Box Patent Application, Washington, DC 20231.

Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it displays a valid OMB control number.

# FEE TRANSMITTAL for FY 2002

Patent fees are subject to annual revision.

## Complete if Known

Application Number	
Filing Date	October 19, 2001
First Named Inventor	SCHETELIG, MARKUS
Examiner Name	
Group Art Unit	
Attorney Docket No.	1117.40738X00

TOTAL AMOUNT OF PAYMENT (\$ 740.00)

## METHOD OF PAYMENT

1. ☐ The Commissioner is hereby authorized to charge indicated fees and credit overpayments to:
- Deposit Account Number 01-2135
- Deposit Account Name Antonelli, Terry, Stout & Kraus, LLP
- ☒ Charge Any Additional Fee Required Under 37 CFR 1.16 and 1.17
- ☐ Applicant Claims small entity status See 37 CFR 1.27

2. ☐ Payment Enclosed:
- ☐ Check ☒ Credit Card ☐ Money Order ☐ Other

## FEE CALCULATION

## 2. BASIC FILING FEE

Large Fee Code	Entity (\$)	Small Entity Fee Code	Fee Description	Fee Paid
101	740	201	Utility filing fee	740.00
106	330	206	Design filing fee	
107	510	207	Plant filing fee	
108	740	208	Reissue filing fee	
114	160	214	Provisional filing fee	

SUBTOTAL (1)

## 1. EXTRA CLAIM FEES

Total Claims	Extra Claims	Fee from below	Fee Paid
11-20**	= 0	18	= 0
Indep. Claims 1-3**	= 0	84	= 0
Multiple Dependent		280	= 0

Large Fee Code	Entity (\$)	Small Entity Fee Code	Fee Description
103	18	203	Claims in excess of 20
102	84	202	Independent claims in excess of 3
104	280	204	Multiple dependent claim, if not paid
109	84	209	** Reissue independent claims over original patent
110	18	210	** Reissue claims in excess of 20 and over original patent

SUBTOTAL (2) \$ 0.00

\*\*or number previously paid, if greater; For Reissues, see above.

## FEE CALCULATION (continued)

## 3. ADDITIONAL FEES

Large Fee Code	Entity (\$)	Small Entity Fee Code	Fee Description	Fee Paid
105	130	205	Surcharge - late filing fee or oath	
127	50	227	Surcharge - late provisional filing fee or cover sheet	
139	130	139	Non-English specification	
147	2,520	147	For filing a request for ex parte reexamination	
112	920*	112	Requesting publication of SIR prior to Examination action	
113	1,840*	113	Requesting publication of SIR after Examiner action	
115	110	215	Extension for reply within first month	
116	400	216	Extension for reply within second month	
117	920	217	Extension for reply within third month	
118	1,440	218	Extension for reply within fourth month	
128	1,960	228	Extension for reply within fifth month	
119	320	219	Notice of Appeal	
120	320	220	Filing a brief in support of an appeal	
121	280	221	Request for oral hearing	
138	1,510	138	Petition to institute a public use proceeding	
140	110	240	Petition to revive - unavaldable	
141	1,280	241	Petition to revive - unintentional	
142	1,280	242	Utility issue fee (or reissue)	
143	460	243	Design issue fee	
144	620	244	Plant issue fee	
122	130	122	Petitions to the Commissioner	
123	50	123	Processing fee under 37 CFR 1.17(q)	
126	180	126	Submission of Information Disclosure Stmt	
581	40	581	Recording each patent assignment per property (times number of properties)	
145	740	246	For each additional invention to be examined (37 CFR § 1.129(a))	
149	740	249	For each additional invention to be examined (37 CFR § 1.129(b))	
179	740	279	Request for Continued Examination (RCE)	
169	900	169	Request for expedited examination of a design application	


Other fee (specify)

\*Reduced by Basic Filing Fee Paid

SUBTOTAL (3) (\$ 0.00)

## SUBMITTED BY

## Complete (if applicable)

Name (Print/Type)	Carl I. Brundidge	Registration No. (Attorney/Agent)	29,621	Telephone	703-312-6600
Signature		Date	10/19/2001		

WARNING: Information on this form may become public. Credit card information should not be included on this form. Provide credit card information and authorization on PTO-2038.

Burden Hour Statement: This form is estimated to take 0.2 hours to complete. Time will vary depending upon the needs of the individual case. Any comments on the amount of time you are required to complete this form should be sent to the Chief Information Officer, U.S. Patent and Trademark Office, Washington, DC 20231. DO NOT SEND FEES OR COMPLETED FORMS TO THIS ADDRESS. SEND TO: Assistant Commissioner for Patents, Washington, DC 20231

---

A method and a device for controlling data extraction from a  
data stream containing at least one data packet

---

09934795-401901

## DESCRIPTION

The present invention relates to a method and a device for data extraction from a data stream containing at least one data packet, in particular for use in a receiver of a wireless digital communication system.

## BACKGROUND OF THE INVENTION

E. g. in TDMA based wireless digital communication systems, like Bluetooth, data is transmitted over an air interface in separate packets with well-defined structure. I. e. data is transmitted in a data stream containing a plurality of data packets. Before a receiver can extract the wanted data out of these packets it has to perform different processing steps.

Signal parameters have to be estimated and appropriate compensation for them has to be done. A synchronization unit, that will be described below, is responsible for the initialization and data extraction in a Bluetooth receiver.

Bluetooth is a global standard for wireless, short-range, low-power, low-cost data communication. On the physical layer a binary, gaussian shaped frequency modulation with low modulation index is used.

Figure 1 shows an example of the receiving chain of a wireless TDMA receiver. After down-conversion of the carrier frequency to an intermediate frequency 1F by a mixer 10, channel selection is done with a channel filter 11. Then after demodulating the waveform in a demodulator 12, the waveform (shown in figure 2 (a) as wavy line W) is transferred into a digital representation (shown in figure 2 (a) as X-es DW) by an AD converter 13. As a consequence a synchronization unit 14, that receives the digital representation of the received waveform, i. e. the digitized demodulated waveform of the received signal at its input, can be fully digital. At its output, that is connected to a link controller 15, it provides the extracted bits of the received data packets for further processing on higher layers.

In order to enable data extraction different tasks have to be performed by the synchronization unit 14.

1 The bits of a data packet are transmitted over an air interface 9 that is represented by an antenna in figure 1, in a sequence of binary FM-modulated symbols. Thus, each symbol represents a received bit. After the FM-demodulation the synchronization unit 14 has to process these symbols as the symbols arrive at the synchronization unit 14 with an unknown timing and unknown DC level.

10 However, for data extraction unknown parameters have to be estimated. The DC level resulting from TX and LO offsets as well as from demodulator 12 deviations can be a few times the amplitude of the waveform itself. Under certain conditions, for example the first connection setup, the timing is totally unknown. For successive packets there is at least a timing uncertainty of  $\pm 10$  symbols.

15 Before data extraction can be started an appropriate initialization for the applied algorithms is required.

20 First of all the presence of a packet has to be detected. When a packet has been detected, the accurate symbol timing needs to be determined. Also a DC estimate needs to be available when data extraction starts.

25 Data extraction requires that for each symbol a 1/0 or a bit decision is made, i.e., it has to be decided whether a symbol represents 1 or 0. Common method for this decision is to slice the waveform i.e. the sequence of symbols with a DC estimate (shown as line DC in figure 2 (a)) into decided but oversampled bits illustrated in figure 2 (b). That is, based on the DC estimate for each of the samples within one symbol a separate bit decision is made. Then for each symbol one sample out of the oversampled bit stream is taken as the result of the actual 1/0 decision. For an optimum bit error rate performance under noisy conditions the samples corresponding to the symbol phase with optimum signal to noise ratio (S/N) (- the so called golden samples -) have to be taken. Figure 2 (c) shows the golden samples taken from the oversampled bit stream by appropriate sampling and the corresponding bits.

35 A DC estimate can be obtained by freezing the output of a low pass filter at an appropriate time instant when a packet has been detected. The position of a

0998495-101901

1 golden sample is assumed to be in the symbol center and therefore can be directly derived from the symbol timing.

5 When data extraction has been started DC estimate and symbol timing estimate may be continuously corrected.

Further, in some known solutions a synchronization unit processes only already sliced bits, i.e. it receives the oversampled bit stream. In this case, DC estimation is done on the radio frequency RF side. However, different DC estimation methods (fast and slow adapting low pass filters) should be used for packet search and data extraction due to different performance requirements. Bit slicing after a false alarm (with a slow adapting low pass filter) is not necessarily correct and a valid packet may be missed therefore.

15 Consequently, receivers have to perform a tradeoff between the packet loss rate (packet not recognized) and the false alarm probability (erroneous indication of a packet). Some receivers simply switch from an unsynchronous scanning mode into a synchronous mode in case a packet has been detected. In case of a false alarm the detection of a valid packet is often blocked then until  
20 the false alarm is recognized on higher layers.

#### SUMMARY OF THE INVENTION

Thus, the object underlying the present invention is to provide a method and  
25 a device for data extraction from a data stream containing at least one data packet that prevents data extraction from being blocked by false alarms.

According to the invention a method for data extraction from a data stream containing at least one data packet, comprises the steps of: comparing a bit  
30 stream derived from a received digital data stream with an expected bit sequence to determine a correlation value for detecting a data packet, starting data extraction when the correlation value exceeds a threshold value indicating that a data packet has been detected, continuing comparing the received bit stream with the expected bit sequence to determine a new correlation  
35 value, and restarting data extraction when the new correlation value exceeds the former correlation value.



1 The present invention makes it possible to highly improve data reception be-  
cause the threshold value for the correlation value that is used to detect the  
data packet can be set relatively low, so that the packet loss rate can be kept  
so low that nearly no data packet is lost whereas false alarm doesn't lead to  
5 receiving invalid data. In case that a data packet is erroneously detected  
while no valid data packet exists, a valid data packet will not be lost, since  
the data packet detection is continuously performed. Thus, in case it is indi-  
cated that a data packet is received that is more likely a valid data packet  
since the correlation value is greater than that of the first data packet, data  
10 extraction is restarted. Therefore, a valid data packet will not be missed even  
if data extraction has already been started due to a false alarm.

To increase the reliability of data extraction according to the present inven-  
tion the threshold value is a programmable value. Therefore, the threshold  
15 value can be adapted to different operational conditions.

To simplify the decision whether a valid data packet has been detected after  
starting data extraction due to a prior data packet detection, it is provided  
that the correlation value is stored as a correlation value each time data ex-  
traction is started or restarted and the new correlation value continuously de-  
20 termined after starting or restarting data extraction is compared with the ac-  
tually stored correlation value.

According to an advantageous refinement of the present invention data ex-  
tracted prior to restarting data extraction is rejected, because data extracted  
25 before restart is apparently false data processed due to an earlier false alarm.

To further improve data extraction an initial timing estimate is determined af-  
ter detecting a data packet but prior to starting data extraction that synchro-  
30 nizes sampling of bits from a data stream for data extraction with data stream  
symbols. The instant when a packet is detected is only a rough timing infor-  
mation and the initial timing estimate further improves data extraction.

According to a preferred embodiment of the present invention, the timing of  
35 the sample process is continuously tracked by comparing the timing of  
symbols within the oversampled bitstream with the actual timing of the sam-  
ple process and correcting the timing of the sample process if the deviation

09931755-101901

1     between the timing of the sample process and the timing of symbols exceeds a  
certain value.

5     According to another aspect of the invention the method for data extraction  
from a data stream containing at least one data packet is preferably per-  
formed by a device that comprises a data extraction unit for extracting data  
from a received data stream, a packet detector for comparing a bit stream de-  
rived from a received digital data stream with an expected bit sequence to de-  
10    termine a correlation value, and a sync-control module receiving the correla-  
tion value from the packet detector that controls the data extraction unit for  
starting data extraction when the correlation value exceeds a threshold value.

15    Due to the packet detector that can be operated independently from the data  
extraction unit, it is possible to continuously perform packet detection even if  
data extraction has already been started. Therefore it is possible to restart  
data extraction as required by the inventive method immediately when a new  
threshold value indicates that a data packet has been detected again, now  
with higher reliability.

20    The device further comprises an initial timing estimator which receives the  
data stream for determining an initial timing estimate prior to starting data  
extraction for synchronizing data extraction with data stream symbols, the  
initial timing estimate is output to the sync-control module.

25    The data extraction unit comprises a DC estimator deriving a DC estimate  
from the received data stream, a comparator for performing a bit decision on  
the data of the received data stream to derive an oversampled bit stream, the  
comparator has first and second inputs for receiving the DC estimate from the  
DC estimator and the data stream, respectively, and a sample-and-hold mod-  
30    ule for sampling the oversampled bit stream received from the comparator.

35    The data extraction unit further comprises a timing estimator receiving the  
oversampled bit stream output by the comparator for tracking the initial tim-  
ing and for controlling the sample-and-hold module.

Since the data extraction unit comprises a timing estimator for continuously  
tracking the timing or synchronization it is possible that the initial timing es-

1     timator can work in the same way as before after starting data extraction, so  
that in case that a further data packet has been detected with higher reliabil-  
ity restarting data extraction can be performed in the same way as starting  
data extraction at the first time.

## 5                   BRIEF DESCRIPTION OF THE DRAWINGS

The present invention will be explained in more detail hereinafter with refer-  
ence to the accompanying drawings showing preferred embodiments.

10     Figure 1 shows a simplified block diagram of the receiving chain of a conven-  
tional transceiver used for wireless communication.

15     Figure 2 shows different diagrams for (a) the demodulated waveform, the digi-  
talized demodulated waveform and the DC level, (b) the oversampled bit  
stream and (c) the extracted bit data stream with the respective bits.

20     Figure 3, a simplified schematic block diagram of a device according to the  
present invention that can be used as synchronization unit.

25     Figure 4, a simplified schematic diagram of a sync-control state machine  
used with the present invention.

30     Figure 5, a simplified schematic block diagram of a timing estimator used in  
a data extraction unit of a synchronization unit according to the present in-  
vention.

## 35                   DETAILED DESCRIPTION OF THE INVENTION

30     The device for data extraction, e.g. a synchronization unit, according to the  
present invention is realized with a highly modular structure. As can be seen  
in Figure 3 the main parts of the synchronization unit are a preprocessing  
module 16 that might contain ADC postprocessing or postdetection filtering of  
the demodulated signal, a packet detector 17 that scans the input signal, i.e.  
35     the digital representation of the demodulated waveform for valid access codes,  
an initial timing estimator 18 that provides an initial estimate of the symbol  
timing, a DC estimator 19 that generates initial as well as continuously

1 tracked DC estimates for symbol slicing, a comparator 20 for symbol slicing, a  
timing estimator 21 for continuously tracking the symbol timing, a sample-  
and-hold module 22 that performs the downsampling, and a sync-control  
module 23 that controls all modules given above.

5 In general, the preprocessing module 16 might contain ADC postprocessing or  
postdetection filtering of the demodulated signal.

10 E. g., the preprocessing module 16 is responsible for postdetection low pass  
filtering is used for optimizing the bit error rate under noisy and interfering  
conditions. Output is the low pass filtered digital waveform representation  
DW of the demodulated waveform W. The preprocessing module 16 is placed  
at the radio frequency/baseband (RF/BB) interface.

15 The packet detector 17 is responsible for indicating the presence of valid pa-  
ckets. The packet detector 17 gets the demodulated and filtered waveform sig-  
nal DW as input and provides a correlation value CorrVal as output signal.  
The correlation value CorrVal indicates the degree of similarity between the  
bit sequence of the received waveform and an expected bit sequence.

20 A packet detector 17 for TDMA transceivers that can be used with the present  
invention is described in detail in the copending U.S. patent application (At-  
torney's Docket No ...) filed on the same day as the present application and  
claiming the priority of the German patent application DE 100 51 889, the  
25 disclosure of which is incorporated in this specification by reference. In this  
application the calculation or the estimation of the correlation value is ex-  
plained.

30 The initial timing estimator 18 also processes the digital demodulated wave-  
form signal DW. During a given search time, indicated by the sync-control  
module 23, the initial timing estimator 18 determines the accurate symbol ti-  
ming. The initial symbol timing estimate is delivered to the sync-control mod-  
ule 23.

35 The DC estimator 19 performs two tasks. Again the digital demodulated wave-  
form signal is processed. By selecting an appropriate sample of an internal  
low pass filter an initial DC estimate is generated. Afterwards this DC estima-

TOP SECRET 56478660

1     te is continuously tracked i.e. in case of a DC drift resulting from a carrier  
frequency drift the DC estimate is continuously corrected. The DC estimate is  
supplied to the comparator 20 for symbol slicing.

5     The comparator 20 simply compares the digital waveform signal DW with the  
DC estimate and performs the symbol slicing by providing the value 1 in case  
that the value of the waveform signal DW is greater than the DC estimate or  
the value 0 in case that the value of the waveform signal DW is less than the  
DC estimate. Therefore, the output of the comparator 20 is an oversampled  
10    stream of bits as shown in figure 2b.

15    The timing estimator 21 continuously tracks the symbol timing estimate. It  
starts with an initial timing estimate that it gets from the sync-control mod-  
ule 23. The timing estimator 21 evaluates the edges of the demodulated wave-  
form which are internally generated by processing the oversampled bit stream  
received from the comparator 20 and compares estimated timing and actual  
timing of the edges. The actual timing may be equal, early or late compared to  
the estimated timing. In case there is a certain tendency towards either early  
or late, the estimated timing is corrected appropriately. The symbol timing es-  
20    timate STE is provided to the sample-and-hold module 22 as output signal of  
the timing estimator 21. The symbol timing estimate STE can be actually  
formed by two signals, wherein the timing information is indirectly coded on  
them.

25    The sample-and-hold module 22 performs the downsampling by taking out  
the golden samples for the symbol decision. The sample-and-hold module 22  
also provides the interface to the following circuits (not shown) which further  
process the extracted data on higher layers. Besides the extracted data B it-  
self, a signal for indicating the data start (FrameSync) is needed also.

30    The sync-control module 23 controls the synchronization process. It is based  
on a state machine where the states correspond to the different phases of the  
synchronization process. With the SyncWin signal higher layers can indicate  
to the sync-control module 23 when a valid packet has to be expected. The  
35    output of the sync-control module 23 is the current state of the internal sta-  
te machine. With the SyncWin signal the other modules of the synchronizati-  
on unit are controlled.

- 1 A detailed description of the synchronization unit focussing on the sync-control state machine and the timing estimation will now be given with reference to figure 4.
- 5 The synchronization process can be split into different phases. These phases are represented by different states of the state machine inside the sync-control module 23. These phases are:
- INIT: All modules are initialized to a well-defined startup state.
- 10 SEARCH PACKET: A valid packet is searched.
- PACKET FOUND: A valid packet has been found.
- SEARCH TIMING: The accurate symbol timing is searched.
- SYNCFIND: The symbol timing, i.e. synchronization, has been found.
- 15 ACTIVE: Data extraction is running, however the search for valid packets is still continued.
- FINISHED: Data extraction is running until the synchronization unit is switched off, no packet search is done anymore.
- 20 When the synchronization unit is switched on, i. e. the clock is running but a signal enable is low, i. e. the signal enable equals 0, the state INIT is entered. Internal registers are reset to default or programmable values. The state INIT is left and the state SEARCH PACKET is entered when the enable signal is set to high, i. e. the enable signal equals 1.
- 25 By entering the state SEARCH PACKET the packet detector 17 as well as the initial timing estimator 18 are enabled. The packet detector 17 delivers a correlation value CorrVal to the sync-control module 23 which indicates the degree of similarity between a bit stream of a received demodulated waveform
- 30 and the expected access code or synchronization word. When CorrVal exceeds a programmable threshold CorrThres the wanted packet is supposed to be found. In this case the state PACKET FOUND is entered in case that the signal SyncWin is high or 1.
- 35 Always when the state PACKET FOUND is entered the latest correlation value CorrVal is stored in a register MaxCorrVal of the sync-control module 23 (not shown).

TOP SECRET

Whenever a new correlation value CorrVal from the packet detector 17 exceeds the registered correlation value MaxCorrVal, while at the same time the state FINISHED has not been reached, while the signal SyncWin is high or 1 the state PACKET FOUND is reentered and MaxCorrVal is set to the new value. I. e., the synchronization process can be restarted in the state PACKET FOUND. As a consequence the synchronization unit can continue with scanning for access codes while data extraction is already prepared or even started. In case the correlation value CorrVal indicates a higher level of confidence (higher correlation value CorrVal) compared to the last packet detection, the synchronization process is restarted. So far extracted data is rejected. Restarting of the synchronization process may be called multiple sync-found.

15 An advantage of multiple sync-founds is that the tradeoff between the false alarm rate and the packet detection performance under noisy conditions is eased, as always the best matching sequence can be detected. False alarms do not block the synchronization unit to detect access codes received with sufficient signal quality. Normally false alarms do not reach the highest possible correlation value `CorrVal` levels

The state PACKET FOUND can only be entered when a signal SyncWin is set to 1. Otherwise the result of the correlation value CorrVal evaluation is ignored. By means of the signal SyncWin higher layers can control the synchronization process. A well-defined time window for synchronization can be given as a consequence.

When the state PACKET FOUND is entered the timing of the detected packet is already roughly known. However the inaccuracy is nearly  $\pm 1$  symbol. As a consequence the initial timing estimator 18 has to search for the accurate timing during one symbol period only. This allows an efficient implementation of the initial timing estimator 18.

35 The state PACKET FOUND is left when the search time for the initial symbol timing estimate starts. The search time starts a programmable time after the state PACKET FOUND has been entered. A counter WinCount is started when the state PACKET FOUND is entered. When the counter WinCount value reaches the programmable value WinStart the state SEARCH TIMING is entered.

- 1 The counter WinCount continues to run in the state SEARCH TIMING. The delay given by value WinStart between packet detection and start of the initial timing search is needed as the packet detector 17 and the initial timing estimator 18 trigger on different parts of the processed access code. The packet  
5 detector 17 triggers at the end of the synchronization word and the initial timing estimator 18 triggers at the end of the trailer bits of the received data packet.

- 10 In the state SEARCH TIMING the sync-control module 23 waits for the trigger signal InitTiming from the initial timing estimator 18. When the trigger signal InitTiming arrives, i. e. when the signal InitTiming equals 1 or when the counter WinCount reaches the programmable value WinStop the state SYNC-FOUND is entered.

- 15 The state SYNCFOUND only lasts for one clock cycle. It indicates to the other modules that an access code with the accurate symbol timing has been found, i.e. that synchronization has been found. The timing estimator 21 and the sample-and-hold module 22 are initialized during the state SYNCFOUND. In these modules 21 and 22 modulo counters with a period corresponding to the  
20 symbol period are started then. The state SYNCFOUND is immediately left. Normally the state ACTIVE is entered. Except for the one condition that the counter CorrVal value exceeds the registered value MaxCorrVal while the signal SyncWin is set. In this case the state PACKET FOUND is entered.

- 25 The state ACTIVE lasts for a programmable time MaxSearchTime. When it is entered the counter AfterSFCCount is started. When this counter AfterSFCCount value exceeds the programmable value MaxSearchTime the state FINISHED is entered.

- 30 During the state ACTIVE as well as during the state FINISHED the data extraction is active. However during the state ACTIVE the synchronization process can be restarted under the known conditions bound to the values CorrVal, MaxCorrVal and SyncWin.

- 35 The state FINISHED is left when the synchronization unit 23 is disabled. In this case the state INIT is entered again when the signal enable is set high. Normally the synchronization unit 14 is switched off inbetween.

090795-1090  
"TOPOT" 5628660



1 The synchronization unit 14 is not responsible for detecting the end of the user data. Higher layers have to stop the data evaluation at the appropriate time.

5 Advantage of the modular structure of the synchronization unit 14 according to the present invention is that the modules for packet detection and symbol timing estimation (packet detector 17, Initial timing estimator 21) can continue to work when the data extraction is already started.

10 For an optimum receiver performance in terms of bit error rate the most appropriate samples within the oversampled bit stream from symbol slicing -the so called golden samples- have to be used to represent the received bits.

15 The task of the timing estimator 21 is to set the sample time for the sample-and-hold circuit 22. After initialization the timing estimator 21 continuously corrects the sampling time. Main reason for the continued correction is to compensate for initial timing errors after synchronization. A second reason is to compensate for deviations between the transmitter and receiver bit clock.

20 The timing estimation is done with an edge detection procedure. That means that the edges of the oversampled data signal from symbol slicing are used to estimate the symbol timing. As the received and filtered symbols are symmetric the so called golden samples are found in the center of each symbol. Due to the symmetry of the symbols the edges are always positioned in the center  
25 between two symbols. Consequently the edges occur with a fixed phase of half a symbol relative to the golden samples.

30 The timing estimation is done in two steps. In the first step for each edge on the data signal from symbol slicing, i. e. the oversampled bit stream, the estimated timing of an expected edge is compared with the actual edge timing. The estimated timing of an expected edge can be generated by delaying the latest sampling trigger by half a symbol. The sampling triggers correspond to the estimated timing of the golden samples. The estimated timing of edges and the estimated timing of golden samples can be regarded as certain phases  
35 of the estimated symbol timing.

0901755-101  
"TOT" 5525660

1 If the estimated edge timing appears to be early an early-late-counter 31 value (cf. Fig.5) is decremented. If it appears to be late the early-late-counter 31 value is incremented. This is done for each actual edge that appears. When  
5 actual edges and estimated edges occur at the same time the early-late-counter 31 value is unchanged. Also when no actual edges occur due to a sequence of equal bits the early-late-counter 31 will keep its value.

In the second step the early-late-counter 31 value is compared to a programmable threshold CorrectionThres. If the positive or negative value of the  
10 early-late-counter exceeds this threshold CorrectionThres the estimated symbol timing is appropriately corrected. With this threshold the adaptation speed of the timing estimation is controlled. After correction of the estimated symbol timing the early-late-counter 31 value is set to 0 again. The early-late-counter value is also set to 0 at initialization in the state SYNCFOUND.

15 Figure 5 shows an example for an implementation of the timing estimation in the timing estimator 21.

20 The estimated edge timing is given with a signal ExpectedEdge that can be internally generated from the current symbol timing estimate, i. e. from the current golden sample timing estimate, by delaying the sample trigger by half a symbol as mentioned above. The bit stream from symbol slicing, i.e. the output signal of the comparator 20, is used in the timing estimator for generating the signal ActualEdge by performing edge detection on this signal.

25 The signal ExpectedEdge and a signal ActualEdge generated by an edge detector 24 are fed each into a tap delay line 25, 26 with a length of roughly half a symbol. The taps of each of the tap delay lines 25, 26 are respectively connected to first and second AND gates 27, 28 via respective OR gates 29,  
30 30. The signal ActualEdge output by the edge detector 24 is fed to a second input of the second AND gate 28 the first input of which receives the output of the second OR gate 30 that is connected with the second tap delay line 26 receiving the signal ExpectedEdge. Similarly, the signal ExpectedEdge is fed to a second input of the first AND gate 27 the first input of which receives the  
35 output of the first OR gate 29 that is connected with the first tap delay line 25 receiving the signal ActualEdge.

1 By respectively comparing each one of the signals ActualEdge and Expected-  
Edge with the delayed taps of the other it is checked if one event (i.e. expected or actual edge) occurred before the other. If so, a corresponding trigger  
5 Early or Late is respectively set and the early-late-counter 31 is appropriately  
changed. Under normal operation ExpectedEdge and ActualEdge events occur  
at maximum only a few samples apart. In addition, ExpectedEdge and Actual-  
Edge events occur at most only once during a period of nearly one symbol.

When the early-late-counter 31 value exceeds the correction threshold Cor-  
10 rectionThres the estimated symbol timing is appropriately shifted one sample  
by incrementing or decrementing the signal SelSampleNo by correction means  
32 associated with early-late-counter 31. I. e., if early-late-counter 31 value  
is less than the negative value of the threshold CorrectionThres the signal  
SelSampleNo is incremented, whereas, when the early-late-counter 31 value  
15 is greater than the positiv threshold CorrectionThres the signal SelSampleNo  
is decremented. The early-late-counter 31 value is then reset to zero again.

The timing estimator 21 as well as the sample-and-hold circuit 22 are initiali-  
zed in the state SYNCFOUND. The state SYNCFOUND occurs with a known fi-  
20 xed phase relative to the received demodulated waveform signal. SelSampleNo  
is a certain phase relative to a free running modulo counter 33 (period 1 sym-  
bol) which is initialized at the SYNCFOUND state. At initialization Sel-  
SampleNo is set to a well-defined value which represents the initially estima-  
ted timing of golden samples. As a consequence the current symbol timing es-  
25 timate is given with the signal SelSampleNo.

The symbol timing estimate STE, i.e. the estimated timing of the golden  
samples is delivered to the sample-and-hold circuit 22 with two signals, i.e.  
the signal SelSampleNo and the output of counter 33. The free running mo-  
30 dulo counter 33, is used as a reference time. The modulo counter 33 is star-  
ted when the sync-control circuit 23 enters the state SYNCFOUND by a start  
signal Start. The second signal SelSampleNo determines the actual sampling  
time. When SelSampleNo and modulo counter 33 value are equal the  
sampling is triggered. When SelSampleNo is incremented by 1 the sample ti-  
35 ming is delayed one sample. When SelSampleNo is decremented by 1  
sampling takes place one sample earlier.

TOP SECRET 56278560

- 
- 1 Purpose of the two-signal solution instead of one sampling trigger signal is to  
deliver besides the actual timing also information about the initial timing to  
the sample-and-hold circuit 22.

5

10

15

20

25

30

35

090479-101901